



USER MANUAL

**ELECTRONIC
VOLTAGE
STABILIZER**

Congratulations on owning a product that is not just thoughtfully designed, but also the most advanced in its category, without a doubt. Every stabilizer is inspected and tested thoroughly before leaving our premises. In case of any manufacturing defect, we undertake to replace the unit during the first 3 months from the date of purchase, provided the same is returned in good condition with scratch-free cabinet and the packaging materials by the customer. Further, we undertake to repair the unit for a balance period of 2 years 9 months of total 3 years warranty. This undertaking does not extend to any equipment connected to the voltage stabilizer.

Model : DIGI 200	Capacity : 6 Ampere	Application : Smart/LED TV above 203 cm (80) + Set Top Box + Home Theatre / Gaming Console or Photostat Machine
-------------------------	----------------------------	--

The most up-to-date design and manufacturing standards make this an ideal guard for your equipment against voltage fluctuations. This stabilizer is equipped with surge and spike protection for the protection of your Smart/LEDTV from input voltage transients. This stabilizer can withstand up to 320V AC input. Please ensure that excess voltage beyond this level is not fed to the stabilizer, which can cause serious damage to the stabilizer and connected equipment, in which case warranty will have no application. This stabilizer is designed to work up to 50°C ambient temperature.

This stabilizer gives a regulated output of 220V \pm 7% for an input range of 170V-275V. In case of high voltage (>275V) at the input, the output rises above the set value (220V+7%) and when the input reaches 295V the stabilizer will cut-off automatically. In case of low input voltages (<170V) the output voltage goes below the set value (220V-7%) and input voltage below 140V the stabilizer will cut-off automatically.

Please follow these simple instructions carefully:

Connect your equipments to the sockets provided on the right side of stabilizer. Plug the three pin top of the stabilizer to the mains. Do not cover the stabilizer with cloth or any other material and ensure that proper ventilation is provided for stabilizer. Make sure that there is no loose connection and proper earthing is done.

This unit is provided with two LED indications namely INPUT and OUTPUT.

Condition	LED Indication		Output Voltage
	INPUT	OUTPUT	
Normal Input Voltage	RED	GREEN	Available
Low / High Voltage Cut-off / Time Delay / High Temperature Cut-off	RED	RED	Not Available
**Overload Cut-off / No Mains Input	OFF	OFF	

The stabilizer will give output automatically when the temperature is reduced or line voltage comes to the working range. This stabilizer is incorporated with an initial time delay of 5 \pm 2 s.

**This stabilizer is provided with thermal overload protection feature. When the internal temperature rise of the product exceeds the pre-set limit due to overloading or misbehaviour of connected equipment the protection acts, and stabilizer goes to OFF hence LED indications will be in OFF condition. Confirm the connected load draws not more than the rated current of this stabilizer and wait for 10-15 min to restart the stabilizer.

Do not connect any other equipment, which draws more than the rated current to this stabilizer.

Switch off stabilizer when TV/ Photostat Machine is not in use.



V-Guard Industries Ltd.,
Registered Office: 42/962,
Vennala High School Road,
Vennala, Kochi - 682028, Kerala.
Ph: 0484-2005000, 4335000
www.vguard.in

SCAN TO AVAIL THE
**DIGITAL
WARRANTY**
BY REGISTERING YOUR
PRODUCT ONLINE



V-Guard Care
0120 485 0100
1860 180 3000
customercare@vguard.in
9633503333



www.vguard.in/home/customer-care
CIN: L31200KL1996PLC010010